

1000A AC/DC Watt Clamp Meter

Model: DT-3353



DT-3353 Professional True RMS 1000A AC Watt Clamp Meter provides accurate Watt, AC Current and Voltage readings regardless of waveforms.

Features:

Analysis for Single Phase and Balanced 3 phase system
True RMS Value (Voltage and Current)
Large dual LCD Display with Backlight
USB interface
Data Hold , MIN / MAX measurement
True power / apparent power / power factor measurement
Auto Ranging & Auto Power Off
Overflow Indication
Manual Data Memory and Read (99 sets)
NCV Detection
2.16" (55mm) Jaw opening

Size (H x W x D): 295mm x 100mm x 46mm

Weight: 537g

1000A AC/DC Watt Clamp Meter

Model: DT-3353


Specifications:

Function	Range	Basic Accuracy
AC Voltage	15V/100V/300V/750V	$\pm(1.2\%+5)$
AC Current	40A/100A/400A/1000A	$\pm(2\%+5)$
True Power	0.60kW—750kW	$\pm(3\%+5)$
Apparent Power	0.60kVA—750kVA	$\pm(3\%+5)$
Reactive Power	0.60kVAr—750kVAr	$\pm(4\%+20)$ of 15V/1000A else $\pm(4\%+5)$
Power Factor	0.3-1	$\pm(2\%+20)$
Phase Angle	0°-90°	$\pm 1^\circ$
Frequency	20Hz-200Hz	$\pm(0.5\%+5)$
Energy	1-9999kWh	$\pm(3\%+2)$

Accessories:

Test leads, gift box with carrying case and 9V battery, USB Cable, CD Software.

Application:



1000A AC/DC Watt Clamp Meter
DT-3353 Professional True RMS 1000A AC Watt Clamp Meter provides accurate Watt, AC Current and Voltage readings regardless of waveforms.

- 1000A True RMS
- DC/AC True Power to 750kW

آدرس: تهران، خیابان مطهری، خیابان میرزای شیرازی شمالی، کوچه نعیمی، پلاک ۱۰، طبقه ۳

تلفکس: 88105813

تلفن: 88482667 --- 88482667

